

Pulse Stretcher

Technical Datasheet



Wiring Diagram:

+12v DC
-12v DC
Com relay contact
N.O. relay contact
N.C. relay contact

Application:

- Extends short pulse from vibration sensors to longer pulse for alarm panel to recognise.

Specifications:

- 12v DC operation.
- Dual input single output.
- Low standby current 5mA.
- Current rating 10A@ 12VDC.
- Adjustable sensitivity on each input.
- Surge protection on inputs.
- Physical size: 50mm x 45mm.

Installation

- Connect 12v dc and sensors.
- Test sensors, relay will energise on each activation.
- Adjust preset clockwise to decrease the sensitivity.

www.comtronix.net

Tel: 011 791 1362/060 384 1775 / **Email:** support@comtronix.net

While every precaution has been taken during the preparation of this document to ensure the accuracy of its content, Comtronix assumes no responsibility for errors or omissions. Comtronix reserves the right to make changes to the product or this document without notice.